

CyberAtom X-201

Main Features

Output Data

Reported output data provides orientation information as:

- Quaternion
- Euler Angles

as well as actual rotation rate over local body axes.

In addition, internal sensor data readings are available in the form of:

- Raw Measurements
- Uncalibrated Measurements
- Calibrated Measurements
- Operating Temperature

Output Data Update Rate

The X-201 device produce orientation data with 100 Hz update rate.

The device can be queried for the estimated orientation data and provide them on demand, or can be commanded to start broadcasting them in an continuous mode.

UART Communication Interface

The device can be controlled over UART interface with configurable baud rate.

The factory default transmissions parameters are 57600 8-N-1.

I2C Communication Interface

The device can be controlled over I2C bus where it acts as a slave device. The clock speed can be up to high-speed rate of 400 kHz.

The factory default I2C slave address for the device is 0x30.

The I2C slave address is configurable and can be changed to any value.

Sensor Calibration

It is possible to easily calibrate standalone as well as assembled device to get best possible performance in it's operational environment.

Calibration takes such things into account as:

- Inertial sensor bias and its temperature drift
- Soft- and hard-iron effect on magnetometer sensor
- Sensor axes missalignments

Performance Tuning

The device has configurable set of parameters that tune internal algorithm and make the sensor data processing to be tailored for specific needs.

Breadboard-friendly Pinout

X-201 comes with pins organized in two rows in a distance and 2.54 mm pitch that is friendly for prototyping with breadboards.

Axes Conventions

CyberAtom device reports its orientation with regards to a reference frame following ENU axes conventions.




Figure 1: Axes Conventions for X-201 device.

Technical Parameters

Table 1: Technical parameters of the device.

Electrical	Value	Unit
Supply Voltage	+3.3	V
Current Consumption	55	mA
Output Logic Level	+3.3	V
Input Logic Level	+3.3 to +5.0	V
Environmental	Value	Unit
Operation temperature	-35 up to +80	°C
Storage temperature	-35 up to +80	°C
Temperature calibration range	+24	°C
Shock survivability	100	g
Accelerometer Sensor	Value	Unit
Data measuerment rate	100	Hz
Scale	4	g
Resolution	16	bits
Magnetometer Sensor	Value	Unit
Data measuerment rate	100	Hz
Scale	2	Gauss
Resolution	16	bits
Gyroscope Sensor	Value	Unit
Data measuerment rate	100	Hz
Scale	2000	deg/sec
Resolution	16	bits
AHRS Output Data	Value	Unit
Maximum output update rate	100	Hz
Quaternion output data format	float IEEE754	
Euler angles output data format	float IEEE754	
Maximum acceleration	±2	g
Maximum rotation rate	2000	deg/sec
Communication	Value	Unit
Communication interfaces	I2C, UART	
Max I2C clock speed	400	kHz
Factory default I2C slave address	0x30	
Max UART baud rate	230400	bauds
Factory default UART baud rate	57600	bauds
Firmware upgrade interface	UART	
Cable connector type	-	
Data Ready output	yes	
Hard reset input line	yes	
Mechanical	Value	Unit
Width	17.78	mm
Height	21.6	mm
Depth	2.5	mm
Weight	2.5	g
Mounting technology	THT	

Mechanical Drawings




Figure 2: Outer dimensions. All values in millimeters.

PCB Footprint




Figure 3: X-201 footprint for PCB design (view from top). All values are in millimeters.

Pin Descriptions




Figure 4: Pin numbering (view from top).

Table 2: Pins and signal names for X-201 device.

Number	Name	Type	Remarks
1	GND	Power Input	Common ground signal.
2	RESET	Input	Resets the device (LOW) or normal operation (HIGH or unconnected).
3	TX	Output	UART (serial) port output line.
4	RX	Input	UART (serial) port input line.
5	DRDY	Output	Is set to LOW when new output data being ready for reading.
6	VDD	Power Input	+3.3V power supply input.
7	NC	n.a	Leave unconnected.
8	NC	n.a	Leave unconnected.
9	SDA	Input/Output	I2C bus data line.
10	SCL	Input	I2C bus clock input.
11	GND	Power Input	Common ground signal.
12	VDD	Power Input	+3.3V power supply input.

Legal Notice

Any information furnished by Softexor and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Softexor materials rests with the end user, since Softexor and its agents cannot be aware of all potential uses. Softexor makes no warranties as to the fitness, merchantability or suitability of any Softexor materials or products for any specific or general uses. Softexor shall not be liable for incidental or consequential damages of any kind. All Softexor products are sold pursuant to the Softexors' Terms and Conditions of sale in effect from time to time, a copy of which will be furnished upon request.

Softexor, the Softexor Logo, and other marks are trade marks or registered trade marks of Softexor S.A or an affiliate company thereof. Other product or service names may be the property of third parties. Nothing herein provides a license under any Softexor or any third party intellectual property rights.

© Copyright 2015 Softexor. All Rights Reserved.